

DATA SHEET












LED WIZARD RGB MANUAL LED CONTROLLER

SKU: SA-CTRL-RGB-MANUAL-CONTROLLER



Product Description

Solid Apollo's LED Wizard RGB Manual LED Controller is specifically designed for controlling RGB LED multicolor change patterns and also has the highest capacity of wattage per channel in its class. You can connect up to a whopping 720W of RGB Lights in one controller and thanks to its 8 function buttons, controlling RGB Lights has never been easier. This Manual RGB LED controller is the perfect solution for RGB LED strips or RGB Lights. The 8 buttons on the RGB Controller consist of different functions that will enable you to set and create your own atmosphere. It has 25 built in color-changing modes to choose from, 64 brightness levels to dim or brighten, 47 speed programs to fasten or slow things down, and of course pause/play when you need it. The RGB Manual Controller has a max current output of 10 amps (red, green, and blue) per channel and operates at 12V or 24V DC. That said, at 12V DC its max output is 360W and at 24V its max output is 720W. More power for your buck.

- 25 Pre-Saved Programs
- Single Color Selection (White, Red, Green, Blue, Cyan, Purple, and Yellow)
- Dimming Available for Single Colors Only
- 64 Color Brightness Adjustment
- 47 Speed Program Adjustment
- Pause / Play Button
- Memory Retention When Power Goes Off
- On/Off Button
- PWM Control (extend lifetime of LED's 100%)
- Stand-by Power Consumption = 0.5W


Quick Spec.


 Dimmable 	Yes
• Input Voltage:	12-24VDC
• Max Power:	360W@12VDC
	720W @ 24VDC
• Warranty:	3 Years

• Weight:	0.45 lb
• Dimensions:	4.76"x3"x1"
• IP Rating:	IP33
• Control System:	PWM
• RGB Channels:	3

Product Color:	Satin Black
 Working Temp: 	-4 - 140F
• Certifications:	CE, RoHS

Technical Diagrams





Companion Products



RGB 5050 72W SKU: SA-LS-RGB-5050-300-24V



RGB 5050 144W SKU: SA-LS-RGB-5050-600-24V